

## Introduction

GRANITE LINK AP is a portable Access Point that generates the default Wi-Fi network necessary to unite together, GRANITE TWO and GRANITE MINI battery packs in a unique Wi-Fi network when operating on the field.

It is assembled in a robust and convenient carrying case suitable for hooking on a belt for easier transportability.

It is battery operated by internal high capacity cells allowing a long operational runtime on the field, and if needed, can conveniently double up as a power bank for mobile devices like smartphones or tablets.



## Description

1	Mini USB charging port: use the cable provided to charge the internal battery from any suitable AC-DC USB adapter or from any suitable USB power outlet
2	Reset button: use a pointed object and press for 5 seconds to reset to factory default in case of erratic behaviour
3	USB port providing 5V-1A suitable for charging portable devices such as Smartphones or small tablets and to be used when in Power Bank mode
4	Battery Level indicator: press the button to display the battery charging status. The display also shows the actual device status: <b>C:</b> Power Bank turned on <b>R:</b> Wi-Fi access Point powering up <b>Wi-Fi:</b> Access Point turned on and data activity present <b>Charging:</b> the internal battery pack is charging <b>Charging complete:</b> the battery is fully recharged
5	3-position sliding switch. From bottom to top: <b>O</b> – Off <b>C</b> – Power Bank: turn on the USB port <b>R</b> – Router: turn off the Wi-Fi access point



## Instructions

Turn the Wi-Fi on and wait approx 20sec for the “BLUESHAPE Granite Link” network to become operative. All the GRANITE TWO and GRANITE MINI batteries will automatically join this network when their internal Wi-Fi module is tuned on and are not connected already to some other preferential network.

In order to read battery data, join this network with any smartphone and tablet having the GRANITE Link App properly installed (supported OS: iOS and Android).

We recommend you charge the internal battery before using the device.

## Specifications

- Wi-Fi 2.4GHz 802.11 b/g/n
- SSID: BLUESHAPE Granite Link
- Password: blueshape00
- Internal battery: Li-Ion 3.6V 10Ah 36Wh
- Cordura-Like case with Velcro straps and rotating hook
- Dimensions: mm 80(w) x 120(h) x 55(d)
- Weight: 270 grams

## Accessories supplied

- 1x Portable Access Point
- 1x Cordura-like case
- 1x Mini USB charging cable
- 1 x Instruction manual